VG7050ECN Evaluation Board Manual

VG7050ECN-EVB

SEIKO EPSON CORPORATION

Evaluation board/kit and Development tool important notice

- 1. This evaluation board/kit or development tool is designed for use for engineering evaluation, demonstration, or development purposes only. Do not use it for other purposes. It is not intended to meet the requirements of design for finished products.
- 2. This evaluation board/kit or development tool is intended for use by an electronics engineer and is not a consumer product. The malfunction by the noise etc. might be caused depending on your use environment. The user should use it properly and in a safe manner.
- 3. Seiko Epson dose not assume any responsibility or liability of any kind of damage and/or fire coursed by the use of it. The user should cease to use it when any abnormal issue occurs even during proper and safe use.
- 4. The part used for this evaluation board/kit or development tool may be changed without any notice.

NOTICE

No part of this material may be reproduced or duplicated in any form or by any means without the written permission of Seiko Epson. Seiko Epson reserves the right to make changes to this material without notice. Seiko Epson does not assume any liability of any kind arising out of any inaccuracies contained in this material or due to its application or use in any product or circuit and, further, there is no representation that this material is applicable to products requiring high level reliability, such as, medical products. Moreover, no license to any intellectual property rights is granted by implication or otherwise, and there is no representation or warranty that anything made in accordance with this material will be free from any patent or copyright infringement of a third party. When exporting the products or technology described in this material, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations. You are requested not to use, to resell, to export and/or to otherwise dispose of the products (and any technical information furnished, if any) for the development and/or manufacture of weapon of mass destruction or for other military purposes.

All brands or product names mentioned herein are trademarks and/or registered trademarks of their respective companies.

©SEIKO EPSON CORPORATION 2014, All rights reserved.

Index

1.	Ov	/erview	1
1.1	1.	System Configuration	1
1.2	2.	Features	1
1.3	3.	Quick Start	1
1.4	4.	VG7050ECN-EVB Block Diagram	2
2.	Fu	Inctional Description	3
2.′	1.	Power Supply	3
2.2	2.	Control by PC	5
2.3	3.	Typical external measurement instruments connection	6
3.	Bo	oard Configuration	7
3.1	1.	Connection	7
3.2	2.	Board layout	8
4.	So	oftware	9
4.1	1.	Required PC condition	9
4.2	2.	Turn Microsoft .NET Framework 3.5 ON	9
4.3	3.	Installation FTDI D2XX Direct Drivers	12
4.4	4.	Installation VG7050EAN_ECN_RegWriter	12
4.	5.	Setting frequencies and registers with VG7050EAN_ECN_RegWriter	13
5.	Sc	hematic	15
6.	Bil	II of Materials	16
7.	Са	aution	17

1. Overview

VG7050ECN-EVB is an evaluation board which customer can set target frequencies by writing registers' data of VG7050ECN. This manual describes evaluation board VG7050ECN-EVB's operation and accompanying software.

1.1. System Configuration

- Hardware : VG7050ECN Eva-Board (VG7050ECN-EVB)
- Software : VG7050EAN_ECN_RegWriter

1.2. Features

- VG7050ECN evaluation with registers setting by I²C bus
- Automatic register value calculation from inputted frequencies.
 (Also user can set registers value directly.)
- Accompanying software (VG7050EAN_ECN_RegWriter)
 Windows7, 8, 8.1 (32 bit, 64 bit) compatible
- Power supply (+2.5 V or +3.3 V) available through USB connection
- Easy PC connection through USB cable

1.3. Quick Start

- Install software (EV7050EAN_ECN_RegWriter) to PC
- Set jumper evaluation board (VG7050ECN-EVB) jumper pins
- Insert VG7050ECN on the socket
- Connect measurement instruments to VG7050ECN-EVB output terminals
- · Connect PC and VG7050ECN-EVB with USB cable.
- Connect external level to Vc terminal (optional)
- Startup VG7050EAN_ECN_RegWriter
- Input target frequencies and transmit register data to VG7050ECN-EVB
- Evaluate target frequencies on the system.

1.4. VG7050ECN-EVB Block Diagram



Figure 1 VG7050ECN-EVB Functional Block Diagram

2. Functional Description

VG7050ECN-EVB is an evaluation kits. Output frequencies are set by transmitting register data from PC to VG7050ECN-EVB through I^2C bus.

2.1. Power Supply

Two power voltage supply ways (to VG7050ECN device on the boards) are available.

- Way1 Through USB cable and regulator on board
- Way2 Direct power supply from external unit

To select supply way, jumpers (JP7, JP8, and JP9) should be set.in the proper way.



Figure 2 Jumpers for Power supply

Way1 Through USB cable and regulator on board

- JP7: short JP9:short
- JP8 1-2short:2.5V, 2-3short:3.3V

Way2 Direct power supply from external unit

- JP7: short
- JP9 :open
- CN1: power supply from external unit

Table1, 2, 3 describe detail power supply condition.

Table 1	VG7050ECN GND (PVSS) setting	(JP7)
---------	------------------------------	-------

VG7050ECN GND terminal level (PVSS)	JP7 Jumper Installation
GND common	Short
GND separate	Open

Table 2 Regulator output level (through USB cable) (JP8)

Supply Voltage [V]	JP8 Jumper Installation
2.5	Connect pin 1 "2.5 V" to center pin 2
3.3	Connect pin 3 "3.3 V" to center pin 2

Table 3 VG7050ECN VDD power supply setting (JP9)

Power Supply Source	JP9 Jumper Installation		
USB	Short		
External Power supply	Open (External power supply is connected to CN1)		

Caution: It is prohibited that external power supply connection to CN1 during JP9 short connection. If external power supply is connected to CN1 in case of JP9 short, power voltage collision might damage the circuitry on the board and PC.

2.2. Control by PC

Software (VG7050EAN_ECN_RegWriter) controls I²C I/F, OE and FSEL on VG7050ECN-EVB. Table 4 describes the jumpers' function in connection with VG7050EAN_ECN_RegWriter.

Jumper	Pin NO.	Signal name	Initial status
JP1 ^{*1}	3	SDA/SCL pull up level	1-2 Short (3.3 V)
JP2	2	OE	Short
JP3	2	SDA	(Controlled by software)
JP4	2	SCL	
JP5	2	FSEL0	
JP6	2	FSEL1	
JP7	2	VG7050ECN GND level	Short (Same as GND)
JP8	3	Regulator output voltage level (Through USB cable)	3-2 Short (3.3 V)
JP9	2	Power supply way	Short (Power from USB)
JP10	2	Vc terminal GND level	Open (GND separate)
JP11	3	OE terminal VDD/GND level	Open (VDD/GND separate)

Table 4 Jumpers setting

*1 JP1 can stay in 1-2 short even VDD voltage drops from 3.3V to 2.5V.

2.3. Typical external measurement instruments connection



Figure 3 Typical measurement instruments connection

3. Board Configuration

3.1. Connection

Table 5 Power Supply

Power	Voltage	remarks
VDD	3.3 V or 2.5 V	Connected to VG7050ECN(socket mounted)'s VDD Connected to CN1 VDD
GND	0 V	Connected to CN1 GND

Table 6 Connectors, terminals, Socket

Connector, Terminal Socket	content	Remarks
CN1	VDD, GND	
VDD	VDD	
GND	GND	
CN2	I/F	
VC	VC	
OE	OE	
SMA1	VG7050ECN output (OUT)	
SMA2	VG7050ECN inverse output (XOUT)	
Mini-USB	USB	
U1	VG7050ECN socket	



3.2. Board layout



Figure 4 VG7050ECN-EVB Board layout

4. Software

Software (VG7050EAN_ECN_regWriter) should be installed into PC for VG7050ECN-EVB operation.

4.1. Required PC condition

- Microsoft Windows 7, 8, 8.1
- USB2.0
- HDD space 1MB
- 1024 x 768 screen resolution or greater
- Microsoft .NET Framework 3.5
- FTDI D2XX Direct Drivers

4.2. Turn Microsoft .NET Framework 3.5 ON

Microsoft .NET Framework 3.5 is required for VG7050EAN_ECN_RegWriter operation.

Microsoft .NET Framework 3.5 is installed in Windows 7 initially and set turn ON. But in case turned OFF, the check box should be ON at Windows Futures. Customer can set by selecting PC control panel and program & function during internet on line.

🖾 Windows Features	×
Turn Windows features on or off	Ø
To turn a feature on, select its check box. To turn a feature off, clear its check box. A filled box means that only part of the feature is turned on.	
🔲 퉬 Active Directory Lightweight Directory Services	*
📧 🔜 퉳 Hyper-V	
🗹 퉬 Internet Explorer 10	∃
📧 📃 퉬 Internet Information Services	
📰 퉬 Internet Information Services Hostable Web Core	
📧 📝 퉬 Media Features	
🗈 📰 퉲 Microsoft .NET Framework 3.5.1	
📧 🔳 퉬 Microsoft .NET Framework 4.5 Advanced Services	
🗄 📃 퉬 Microsoft Message Queue (MSMQ) Server	
📰 퉬 Network Projection	
📧 🔳 퉬 Print and Document Services	
📰 퉬 RAS Connection Manager Administration Kit (CMAK)	*
OK Can	cel

Figure 5 Microsoft .NET Framework 3.5 Turn ON (Windows 7)

In case of Windows 8/8.1, Microsoft .NET Framework 3.5 is installed initially, but set turn OFF. Two ways are available to turn ON Microsoft .NET Framework 3.5 during internet on line.



- 1. Installation of Microsoft .NET Framework 3.5 on demand
 - At initial starting time of VG7050EAN_ECN_RegWriter, next massage box is shown. Click "Install this feature" for installation during internet on line.

🍚 🖪 Windows Features	×
An app on your PC needs the following Windows feature: .NET Framework 3.5 (includes .NET 2.0 and 3.0)	
😽 Install this feature	
Skip this installation Your apps might not work correctly without this feature.	
Tell me more about this feature	
	Cancel

Figure 6 Microsoft .NET Framework 3.5 turn ON (Windows 8/8.1, on demand)

 Microsoft .NET Framework 3.5 turn ON with PC control panel Customer can set turn ON by selecting PC control panel and program & function during internet on line.



Figure 7 Microsoft .NET Framework 3.5 turn ON (Windows 8/8.1, Control Panel)

Please refer to Microsoft site Windows 8/8.1 Microsoft site

4.3. Installation FTDI D2XX Direct Drivers

An adequate device driver is automatically installed when VG7050ECN-EVB is connected to PC USB terminal during internet on line condition.

If automatic installation is not executed, customer can install device driver by FTDI setup executable.

- 1. Disconnect VG7050ECN-EVB from PC USB terminal.
- 2. Down load setup executable on FTDI WEB site FTDI
- 3. Click the right mouse button "setup executable" and "Run as administrator".



Figure 8 Execution FTDI setup executable

4.4. Installation VG7050EAN_ECN_RegWriter

Install software (VG7050EAN_ECN_RegWriter) to PC by installer (VG7050EAN_ECN_Installer.msi).

4.5. Setting frequencies and registers with VG7050EAN_ECN_RegWriter

Product selection

Select VG7050ECN with radio button.

Setting I²C slave address

Input I²C Slave Address with hex format. If it is unknown, press Search Addr button and found automatic search result.

Frequencies setting

4 frequencies are set into VG7050ECN.

Select a number (0~3) of Frequency Setting NO. column. Input target frequency into Output Frequency column. Registers are calculated automatically.

Kv value selection

Select Kv value (0~11) on Kv column. If larger value (12~) is selected, Vc control function becomes inactive.

Registers' value writing and verification

Registers data is transmitted to VG7050ECN by pressing Write button. Write and Verify button works register's data transmission and verifying between VG7050EAN_ECN_RegWriter and VG7050ECN device on the board. Result is shown in History column.

OE, FSEL port control

OE, FSEL port are controlled by radio button respectively.

Advanced operation

Register reading : VG7050ECN device registers data is transmitted and displayed on Register Read Table.

Frequency calculation from Register: By inputting Register value (hex code), customer can obtain frequency in Output Frequency column.

Reference frequency adjustment: Customer can change any reference frequency by selecting Advanced Mode from Tool pull down menu.



e(F) Tool (T) Help(H)					
odel			Register (Road Table	
O VG7050EAN I2C Slave	Address (Hex)	37 Search Addr			
VG7050ECN Reference	Frequency	14 144444 [MH7]	Addr	value	믝
		[winz]	00	00	-4
equency Setting			OD	00	-0
			OE	00	-8
Frequency Setting No. 0			OF	00	_
			10	09	
Output Frequency	152.24	50000 [MHz]	11	1A	
output requerty	132.2.	Tuniel	12	AD	
Register Regist	or Register		13	3D	
Address Nam	e Value [Hex]	Divider	14	E1	
			15	00	
0x10 ODIV_	09	20 🗸	16	00	
0.11 NINT /		20	17	00	
) IA	20	18	00	
0x12,0x13,0x14 NFRAC	_0 AD3DE1	0.67672545	19	00	
			ſ	Read	
v 5 🚔		Write and	l i i i i i i i i i i i i i i i i i i i		
		Write Verify	Port		
			FSEL	OE	
tory			00b 00b	H	
7050EAN_ECN_RegWriter\2.0.1.0	VG7050_EAN_ECN_RegW	/riter.xml, done.	0.01	<u>.</u>	
te Addr 0x20: 0x0F 0x18 0x87 0x	C3 0x33		© 01b	ΟL	
te Addr 0x30: 0x09 0x1B 0x60 0x	A9 OxDC		10b		
te Addr 0x40: 0x0A 0x1A 0x48 0x	51 0x25				
te Addr 0x15: 0x04		E	© 11b		
npare Match.					
ister Read Done					

Figure 9 VG7050EAN_ECN_RegWriter operation panel

VG7050ECN-EVB

EPSON

5. Schematic





6. Bill of Materials

No	maker	device	code	instance	qty	specification
1	MURATA	capacitor	GRM32NF11E106Z	C1, C2, C3	3	3225, 10 μF ±10%, DC10 V
2	MURATA	capacitor	GRM188B31E105K	C4, C5	2	1608, 1 μF ±10%, DC10 V
3	MURATA	capacitor	GRM188B11E104K	C6, C7, C8, C9, C10, C11, C12, C13, C14, CO1, CO2	11	1608, 0.1 μF ±10%, DC25 V
4	KOA	resistor	RK73H1JTTD5102F	R1A	1	1608, 51 kΩ ±1%
5	KOA	resistor	RK73H1JTTD1003F	R1B	1	1608, 100 kΩ ±1%
6	KOA	resistor	RK73H1JTTD4702F	R1C	1	1608, 47 kΩ ±1%
7	КОА	resistor	RK73H1JTTD1803F	R2	1	1608, 180 kΩ ±1%
8	KOA	resistor	RK73H1JTTD1500F	R3, R4	2	1608, 150 Ω ±1%
9	KOA	resistor	RK73H1JTTD1002F	R5, R6	2	1608, 10 kΩ ±1%
10	Emerson Network Power Connectivity Solutions	SMA	142-0701-851	SMA1, SMA2	2	-
11	MiS Technologies	Socket	CXP-A08-11-00	U1	1	-
12	Linear Technology	regulator	LTC3025	U3	1	2 mm x 2 mm, DFN
13	Texas Instruments	Level shifter	SN74AVC4T245D	U4	1	SOP
14	MAC8	Wrapping terminal	WL-1	CN1, CN2, JP1, JP2, JP3, JP4, JP5, JP6, TP (SDA, SCL, FSEL0, FSEL1)	-	-
15	MAC8	Check pin	LC-22-G- red	VDD	1	red
16	MAC8	Check pin	LC-22-G-yellow	PVSS, OE, VC	3	yellow
17	MAC8	Check pin	LC-22-G-black	TP_GND	1	black
18	FTDI	FTDI module	UM232H	U2	1	-
19	RS	spacer	325-659	-	4	M3 x 12.7 mm nylon

7. Caution

It is prohibited that external power supply connection to CN1 during JP9 short connection. If external power supply is connected to CN1 in case of JP9 short, power voltage collision might damage the circuitry on the board and PC.

Evaluation Board Manual

AMERICA

EPSON ELECTRONICS AMERICA, INC.

HEADQUARTER	214 Devcon Drive, San Jose, CA 95112, U.S.A. Phone: (1) 800-228-3964 FAX: (1) 408-922-0238 <u>http://www.eea.epson.com</u>
Chicago Office	1827 Walden Office Square. Suite 520 Schaumburg, IL 60173, U.S.A. Phone: (1) 847-925-8350 Fax: (1) 847-925-8965
El Segundo Office	1960 E. Grand Ave., 2nd Floor, El Segundo, CA 90245, U.S.A. Phone: (1) 800-249-7730 (Toll free) : (1) 310-955-5300 (Main) Fax: (1) 310-955-5400

EUROPE

EPSON EUROPE ELECTRONICS GmbH

Riesstrasse 15, 80992 Munich, Germany Phone: (49)-(0) 89-14005-0 Fax: (49)-(0) 89-14005-110 http://www.epson-electronics.de

ASIA

EPSON (China) CO., LTD.	7F, Jinbao Building No.89 Jinbao Street Dongcheng District, Beijing 100005, China Phone: (86) 10-8522-1199 Fax: (86) 10-8522-1120					
Shanghai Branch	http://www.epson.com.ch/ed/ 7F, Block B, High-Tech Building, 900 Yishan Road, Shanghai 200233, China Phone: (%) 21.5423.5577 Exx: (%) 21.5432.4677					
Shenzhen Branch	12F, Dawning Mansion, Keji South 12th Road, Hi-Tech Park, Shenzhen 518057, China Phone: (86) 755-2699-3828 Fax: (86) 755-2699-3838					
EPSON HONG KONG LTD.						
	Unit 715-723 7/F Trade Square, 681 Cheung Sha Wan Road, Kowloon, Hong Kong Phone: (86) 755-2699-3828 (Shenzhen Branch) Fax: (86) 755-2699-3838 (Shenzhen Branch) <u>http://www.epson.com.hk</u>					
EPSON TAIWAN TECHNOLOGY & TRADING LTD.						
	14F, No.7, Song Ren Road, Taipei 110					
	Phone: (886) 2-8786-6688 Fax: (886) 2-8786-6660 http://www.epson.com.tw/ElectronicComponent					
EPSON SINGAPORE PTE. LTD.						
	No 1 HarbourFront Place, #03-02 HarbourFront Tower One, Singapore 098633.					
	Phone: (65) 6586-5500 Fax: (65) 6271-3182					
	http://www.epson.com.sg/epson_singapore/electronic_devices/electronic_devices.page					
SEIKO EPSON CORPORATION KOREA Office						
	5F (63Bldg., Yoido-dong) 50, 63-ro, Yeongdeungpo-gu, Seoul 150-763 Korea					
	Phone: (82) 2-784-6027 Fax: (82) 2-767-3677					
	nttp://www.epson-device.co.kr					

SEIKO EPSON CORPORATION

Distributor

Electronic devices information on WWW server

http://www5.epsondevice.com/en/quartz/index.html